

Installation Guide

LUZ® Panel Luminaire Pendant Mount

Important Safety Instructions

Read and follow these warnings and instructions before installing or maintaining this product.

- **WARNING** – Risk of fire or electric shock. To avoid electrical shock or fixture damage turn off power at the electrical panel prior to installation or maintenance.
- Warranty is void in case of unauthorized modifications and/or improper use. Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
- This product must be installed by a person familiar with the construction and operation of the product and the hazards involved, in accordance with the applicable NEC code.
- Do not install damaged product.
- Save these instructions and refer to them when additions, changes or services to the fixture or system are made.



Tools Needed

- Screwdriver – Flat blade
- Screwdriver – Phillips #1
- Standard electrical tools
- Cable cutter
- Level

Installation Guide

LUZ® Panel Luminaire Pendant Mount

1. POWER

- Disconnect your electrical power before installation. Never perform any work on a live circuit.

2. REMOVE EXISTING COMPONENTS

(if applicable)

- Remove existing fixture and dispose of properly.

3. CANOPY ASSEMBLY

- Thread cable through couplers. Pull through to half ball end.
- Attach couplers to canopy using 1/4-20 pan head screws.
- Thread nipple into crossbar and secure to ceiling junction box.

4. SUSPENSION CABLE ASSEMBLY

- Thread loose end of suspension cable through cable grippers and set approximate fixture height.

5. WIRING AND MOUNTING

- After height has been determined, pass loose end of cord through large hole in canopy.
- Trim cord if too long.
- Strip jacket of power cord exposing 4" of inner wires.
- Strip conductors 3/8".
- Connect building wires to fixture cord with appropriate connectors.
- Slide canopy over nipple and fasten with cap nut.
- Wrap strain relief around cord and insert strain relief through canopy.

6. HEIGHT ADJUSTMENT

- Pull cable through until desired height is achieved. Depress pin atop cable gripper to lengthen cable.
- Level fixture in both directions.
- Trim cable leaving 1/4" exposed or coil excess cable and secure to fixture with zip ties.
- Secure cord to suspension cable with zip ties.

